

AMD CPU Support List



Testing Environment:

Memory : KINGSTON DDR3 1333/1G * 2 Pcs

VGA Card : onboard with 256MB, default clock 550MHz

1. Check BIOS CPU ID/Name/Vcore
2. Power On/Off and Reset on different CPU(5 times)

Model: PI-AM3RS785G

updated: 2009/8/27

Processor	Core Name	CPU Code	CPU No	FSB	Frequency	L2 Cache	L3 Cache	Stepping	Wattage
Athlon II X2	Regor	ADX250OCK23GQ	x250	200	3	2M	N/A	C2	65
Athlon II X2	Regor	ADX245OCK23GQ	x245	200	2.9	2M	N/A	C2	65
Athlon II X2	Regor	ADX240OCK23GQ	x240	200	2.8	2M	N/A	C2	65
Athlon II X2	Regor	AD235EHDK23GQ	235e	200	2.7	2M	N/A	C2	45
Athlon II X2	Regor	AD240EHDK23GQ	240e	200	2.8	2M	N/A	C2	45
Athlon II X2	Regor	ADX215OCK22GQ	x215	200	2.7	1M	N/A	C2	65
Athlon II X2	Regor	ADX255OCK23GQ	x255	200	3.1	2M	N/A	C2	65
Athlon II X3	Rana	AD400EHDK32GI	400e	200	2.2	1.5M	N/A	C2	45
Athlon II X3	Rana	AD405EHDK32GI	405e	200	2.3	1.5M	N/A	C2	45
Athlon II X3	Rana	ADX435WFK32GI	x435	200	2.9	1.5M	N/A	C2	95
Athlon II X3	Rana	ADX425WFK32GI	x425	200	2.7	1.5M	N/A	C2	95
Athlon II X4	Propus	AD600EHDK42GI	600e	200	2.2	2M	N/A	C2	45
Athlon II X4	Propus	AD605EHDK42GI	605e	200	2.3	2M	N/A	C2	45
Athlon II X4	Propus	ADX620WFK42GI	x620	200	2.6	2M	N/A	C2	95
Athlon II X4	Propus	ADX630WFK42GI	x630	200	2.8	2M	N/A	C2	95
Phenom II X2	Callisto	HDX545WFK2DGI	x545	200	3	1M	6M	C2	80
Phenom II X2	Callisto	HDZ550WFK2DGI	z550	200	3.1	1M	6M	C2	80
Phenom II X3	Heka	HDZ720WFK3DGI	720	200	2.8	1.5M	6M	C2	95
Phenom II X3	Heka	HDX710WFK3DGI	710	200	2.6	1.5M	6M	C2	95
Phenom II X3	Heka	HD700EOCK3DGI	700e	200	2.4	1.5M	6M	C2	65
Phenom II X3	Heka	HD705EOCK3DGI	705e	200	2.5	1.5M	6M	C2	65
Phenom II X3	Heka	HDZ740WFK3DGI	z740	200	3	1.5M	6M	C2	95
Phenom II X3	Heka	HDX720WFK3DGI	x720	200	2.8	1.5M	6M	C2	95
Phenom II X4	Deneb	HDX810WFK4FGI	810	200	2.6	2M	4M	C2	95
Phenom II X4	Deneb	HDX925WFK4DGI	925	200	2.8	2M	6M	C2	95
Phenom II X4	Deneb	HDX910WFK4DGI	910	200	2.6	2M	6M	C2	95
Phenom II X4	Deneb	HDX805WFK4FGI	805	200	2.5	2M	4M	C2	95
Phenom II X4	Deneb	HDX945FBK4DGI	945	200	3	2M	6M	C2	125
Phenom II X4	Deneb	HDZ955FBK4DGI	955	200	3.2	2M	6M	C2	125
Phenom II X4	Deneb	HD900EOCK4DGI	900e	200	2.4	2M	6M	C2	65
Phenom II X4	Deneb	HD905EOCK4DGI	905e	200	2.5	2M	6M	C2	65
Phenom II X4	Deneb	HDX945WFK4DGI	x945	200	3	2M	6M	C2	95
Phenom II X4	Deneb	HDX820WFK4FGI	x820	200	2.8	2M	4M	C2	95
Phenom II X4	Deneb	HDZ965FBK4DGI	z965	200	3.4	2M	6M	C2	140
Phenom II X4	Deneb	HDX955FBK4DGI	x955	200	3.2	2M	6M	C2	125
Sempron	Sargas	SDX140HBK13GQ	x140	200	2.7	1M	N/A	C2	45